

PATENT
5201-24200
01-006

CERTIFICATE OF EXPRESS MAIL
UNDER 37 C.F.R. § 1.10

"Express Mail" mailing label no. EL893865922US

DATE OF DEPOSIT: June 21, 2001

I hereby certify that this paper or fee is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" Service Under 37 C.F.R. § 1.10 on the date indicated above and is addressed to: Commissioner for Patents and Trademarks, **BOX PATENT APPLICATION**, Washington, D.C. 20231



Derrick Brown

WAFER HOLDER FOR BACKSIDE VIEWING, FRONTSIDE PROBING
ON AUTOMATED WAFER PROBE STATIONS

By:

Jeff E. Blackwood
1424 SE 30th Ave.
Portland, OR 97202

BACKGROUND OF THE INVENTION

1. Field of the Invention

5 This invention relates to semiconductor device electrical test systems, and more particularly to semiconductor device electrical test systems that allow for backside viewing of a semiconductor device while electrically probing its frontside.

2. Description of the Related Art

10 The following descriptions and examples are not admitted to be prior art by virtue of their inclusion within this section.

15 A wafer fabrication process typically forms multiple identical integrated circuits upon and within frontside surfaces of each of several semiconductor wafers processed as a group (i.e., lot). Each individual integrated circuit is formed within a die area of one of the semiconductor wafers. Following wafer fabrication, the dice are subjected to "wafer sort" electrical testing, then separated from the wafers. Fully functional die are typically packaged and sold as individual semiconductor devices.

20 Wafer sort electrical testing is performed to ensure each integrated circuit functions properly according to a predetermined electrical specification. Following wafer fabrication, each wafer is typically placed, with the frontside surface of the dice facing up, upon a flat surface of a test system such as a wafer holder that can move in three-
25 dimensions. A wafer under test is raised up by a translation stage until bonding pads of one of the integrated circuits contact fine probe needles of the test system. The test system may provide electrical power to the integrated circuit via some of the probe needles, and may provide input signals and/or receive output signals from the integrated circuit via other test probe needles. The wafer under test may be automatically lowered,
30 repositioned, and raised again until all of the integrated circuits formed on the wafer

under test have been tested via an automated probe station. A microscope may be mounted above the wafer surface to view the frontside surface of the wafer, where the microscope can be adapted for optical scanning of the die for photoemission-generating defects.

5

In recent years there has been an increase in the overall density of metal used in many integrated circuits near or at the frontside surface. This trend has led to the difficulty of optically detecting photoemission-generating defects of the dopant and thin-film areas that lie beneath the metal layers. Accordingly, it is difficult to scan the frontside surface of the individual die on the wafer. Flip-chip technology has compounded this problem. Flip-chip technology has become increasingly popular during the last few years, as the demand for more efficient and higher-density packaging of integrated circuits has markedly increased. The individual die, in the case of flip-chip technology, are manufactured to have the input/output (I/O) bonding pads of the die placed in a two-dimensional array across the frontside of the integrated chip as opposed to being placed on the perimeter of the die as found in conventional peripheral-terminal device dies. The flip-chip manufactured die in the process of being packaged is inverted (hence the term "flip-chip") and the I/O pads of the die are solder-bump attached to a corresponding array of bonding pads on an upper surface of a packaging substrate. The packaging of flip-chip die save space on the packaging substrate, which allows for higher integrated circuit density packing, and the solder-bumps attachments allow for more efficient electrical coupling between the integrated circuits and the packaging substrate. However, the two-dimensional array of metal I/O pads on the frontside surface of the flip-chip die essentially precludes frontside viewing for photoemission-generating defects as done on existing conventional automated probe stations.

It is then desirable to provide a means for backside viewing of the wafer for optical scanning of photoemission-generating defects. A benefit would arise is such can be accomplished on existing frontside viewing and frontside probing automated probe stations.. The desired backside viewing should be accomplished by inverting the wafer

instead of inverting the microscope, because inverting the microscope would further require a completing re-engineering of the existing frontside viewing automated probe stations to allow for an unobstructed view of the backside surface of the wafer.

5

SUMMARY OF THE INVENTION

10 The problems outlined above may be in large part addressed by an improved integrated circuit test apparatus with a holder that is coupled to a three-dimensional translational mechanism. The holder is preferably adapted to receive a wafer that is inverted so that electrical probing can occur on the frontside of the wafer while the backside of the wafer can be concurrently viewed with an optical scanning mechanism configured above the test apparatus. According to one embodiment, the three-dimensional translational mechanism may be from a pre-existing probe station, i.e., one that probes the frontside while viewing the frontside of the wafer. The integrated circuit

15 test apparatus includes at least one electrically conducting probe needle for establishing electrical contact with the input/output (I/O) bonding pads of the individual die of the wafer undergoing testing. There may be as many as four or more probe needles used to make contact with the wafer. The three-dimensional translational mechanism allows for the movement of the holder in the x, y, and z directions for moving the wafer relative to

20 the electrically conducting probe needles. In accordance with a specification of the layout of the dice on the wafer, the three-dimensional translational mechanism may be further configured to automatically step or reposition the wafer after probing an individual die to move to the next die in succession for automated multi-die probing of any select number of dice on the wafer.

25

The electrical conducting probe needles are each preferably attached to a probe base, where the probe base is configured to allow for the adjustment of the probe needles to align with I/O pads of a die to undergo probe testing. The probe base is in electrical communication with an external integrated circuit testing unit and power supply. In

30 another embodiment, the probe needles may originate from a probe card. The optical

scanning mechanism is adapted to detect photoemission-generated defects of the integrated circuits in the wafer by scanning the backside surface of the wafer that is undergoing frontside electrical probe testing. The optical scanning mechanism may include, among other things, a magnifying and focusing lens, an electromagnetic radiation beam source or electron beam source, and a microscope, where the microscope may be is a charged coupled device (CCD).

In addition to the testing apparatus discussed above, a method for testing an integrated circuit is contemplated herein. The method for testing an integrated circuit on a wafer may include holding the wafer in an inverted position with a holder. Electrically conducting probe needles are used to probe integrated circuits with I/O bonding pads on a frontside surface of the wafer and while optically scanning the backside surface of the wafer, and moving the wafer in the interim between each probing operation.

Moving the wafer in the interim between each probe operation is achieved by using a three-dimensional translational mechanism coupled to the holder, which allows the wafer that is retrofittedly attached to the holder to be moved in the x, y, and z directions. The three-dimensional translational mechanism may be configured in accordance with a specification of the layout of the die on the wafer, to incrementally step or automatically move from the last die tested to the next die on the wafer for any select number of die on the wafer.

Optically scanning the backside surface of the wafer is accomplished by an optical scanning mechanism, where the optical scanning mechanism may scan the backside of the wafer with a beam of electromagnetic radiation. The beam of electromagnetic radiation may be a beam of infrared radiation, since the backsides of wafers typically consists of single crystalline silicon, which is readily transparent to this wavelength of radiation. The optical scanning mechanism is adapted to determine defect-generated photoemissions as viewed from the backside while the integrated circuits undergoing electrical probe. The photoemission-generated defects may indicate the source and type

Fig. 2 is a partial cross-sectional view of a non-automated integrated circuit test apparatus, which allows for backside viewing while probing the frontside surface of a wafer;

5 Fig. 3 is a partial cross-sectional view of an automated integrated circuit test apparatus, which allows for backside viewing while probing the frontside surface of a wafer.

10 While the invention is susceptible to various modifications and alternative forms, specific embodiments thereof are shown by way of example in the drawings and will herein be described in detail. It should be understood, however, that the drawings and detailed description thereto are not intended to limit the invention to the particular form disclosed, but on the contrary, the intention is to cover all modifications, equivalents and alternatives falling within the spirit and scope of the present invention as defined by the
15 appended claims.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Turning to the drawings, exemplary embodiments of a method for testing
20 integrated circuits on a wafer are shown. Fig. 1a is a partial cross-sectional view of an integrated circuit test apparatus 10 for frontside viewing while conducting automated frontside probing of a wafer, which includes holder 60 mounted to three-dimensional translational mechanism 70. Holder 60 is designed to receive and retain a backside bottom surface of a wafer 64 to be tested by typically applying vacuum pressure from the
25 upper surface of holder 60 to the backside bottom surface of wafer 25. Probe station housing 80 provides base support to integrated circuit test apparatus 10. Platen 50 is suspended above holder 60 and has a generally circular opening 55, which allows probe needles 40 and optical scanning mechanism 20 to have access to the frontside of the wafer to be tested.

30

Probe needles 40 are electrically conductive probes that are to be positioned where the end of probe needles 40 makes electrical contact with input/output (I/O) bonding pads of an individual die on the frontside upper surface of wafer 25. Probe needles 40 are shown to originate from probe bases 30 where probe bases 30 may include

5 micropositioning adjusters, which allow for fine adjustment of probe needles 40 in the x, y, and z directions. Camera 21 is preferably attached to platen 50 and enables one to view probe needles 40 for positioning probe needles 40 and/or the wafer. There may be as many as four or more probe bases 30, each with an individual probe needle 40 for testing the wafer. The probe needle or needles could originate from a probe card, which
10 typically has many probe needles emanating around its circumference for probing the wafer. Furthermore, either probe bases 30 or a probe card is electrically connected to a testing control unit 52, which provides electrical power/grounding and sends/receives other electrical signals for testing of the integrated circuits on the wafer.

15 Three-dimensional translational mechanism 70 coupled to holder 60 allows for the movement of the wafer undergoing testing in the three independent x, y, and z directions. Furthermore, three-dimensional translational mechanism 70 is electrically connected to testing control unit 52, which allows for the automatic positioning of the individual die to be tested on the wafer by moving holder 60 up and down in the z-plane
20 and incrementally stepping it a predetermined distance in the xy-plane. Typically, the automated probing process begins with the probe needles 40, which may be finely adjusted by said micropositioner adjusters to make initial contact with appropriate I/O bonding pads of a specific predetermined starting die to be tested on the wafer.

25 Connected to translational mechanism 70 is preferably a motor. The motor, when energized, moves holder 60 in the x, y, or z directions. Typically, mechanism 70 is situated such that probe needles 40 are placed in a "home" position on the wafer above a given integrated circuit. Before placing the wafer in a home position, it must be assured that when mechanism 70 moves in x direction, incrementally across the wafer, the probe
30 needle strikes corresponding probe pads consistently across the wafer for each respective

die. This implies that camera 21 be used in conjunction with a set-up procedure, where mechanism 70 scans back and forth in an x direction, and an operator via camera 21 measures the amount of differences registered in the y direction. Once the y-direction differences are removed by the operator manually rotating holder 60, mechanism 70 is said to be calibrated in the x direction. Of course, the aforementioned calibration technique represents only one of possibly numerous ways to register probe needles on bonding pads in a consistent (calibrated) step-and-repeat fashion.

Once calibrated, the dimensions of each die are entered into the motor connected to mechanism 70. Thereafter, holder 70 is moved in the y direction to register probe needles 40 directly above the corresponding bonding pads of the integrated circuit on wafer 25. This is generally done when the wafer is in the home position. Thereafter, automated probe can take place, beginning at the home position and incrementing the pre-measured distance across the wafer to the next integrated circuit, moving mechanism 70 in the y direction, making contact between the bonding pads and the probe needles, forwarding the stimulus current and voltage to the probe needles, and measuring the resulting values from the probe needles. This is repeated automatically between each integrated circuit across the entire wafer, with defective integrated circuits being noted. The defective integrated circuits will be noted as those which will not be packaged for shipment to a customer.

Optical scanning mechanism 20 is adapted for photoemissions microscopy, wherein it may include, *inter alia*, a magnifying and focusing lens, an electromagnetic radiation source, and a camera, where the camera may be a charged coupled device (CCD) camera. Optical scanning mechanism 20 is positioned over the wafer so as to be in view of the die that is undergoing testing. In an embodiment the dice are electrically test probed with probe needles 40 in contact with the frontside dice I/O contacts to provide grounding and powering up of the integrated circuits to ready or standby condition, and/or activate the circuits. If probe testing notes a defective integrated circuit and/or a non-functional test outcome, then photoemission analysis will be performed.

Photoemission analysis involved optically scanning the frontside surface with either a beam of electromagnetic radiation or electrons in order to detect photoemission-generated defects such as shorts, juncture leakages, pinhole defects in the oxide layers, latch-up, hot-carrier gate generation, etc.

5

Fig. 1b is a partial view of a frontside surface of wafer 25 of Fig. 1a. Section 26 shows the individual die on wafer 25. Fig 1c is an exploded view of portion 26a of wafer 25, which shows a frontside surface of individual die 27. Die 27 is depicted as a flip chip designed die with a two-dimensional array of I/O bonding pads 28 placed across the frontside surface of die 27. Die 27 has probe needles 40 contacting some of its I/O bonding pads 28 for illustrating said frontside probing of an individual die. In another embodiment die 27 may be a peripheral terminal device with I/O bonding pads placed on the perimeter of the die.

10

15

Fig. 2 is a partial cross-sectional view of integrated circuit test apparatus 210 adapted for backside viewing while conducting frontside probing of a wafer. Probe station housing 280 is a base support for integrated circuit test apparatus 210. Holder 260 is designed to receive and retain an outer perimeter of a frontside surface of inverted wafer 225. This can be achieved by using attachment tabs or may be by applying vacuum pressure from the upper surface of holder 260 to the outer perimeter of the frontside surface of inverted wafer 225. Furthermore, holder 260 has circular opening 265 in the middle of it in order to allow probe needle 240 access to the frontside surface of inverted wafer 225. Probe needle 240 is an electrically conducting probe. During testing of the wafer, probe needle 240 is positioned to make electrical contact with an I/O bonding pad on the frontside surface of inverted wafer 225. Probe needle 240 is shown to originate from probe base 230, where probe base 230 may include micropositioning adjusters, which allow for fine adjustment of probe needle 240 in the X, Y, and Z directions.

20

25

Camera 221 is preferably attached to platen 250 in order to be able to view probe needle 240 in relationship with the wafer for positioning probe needle 240 and/or inverted wafer 225 relative to one another. There may be as many as four or more probe bases 230 each with an individual probe needle 240 for testing the wafer. The probe needle or
5 needles could originate from a probe card which has many probe needles emanating around its circumference for probing the wafer. Furthermore, either probe bases 230 or a probe card is electrically connected to a testing control unit 252, which provides electrical power and grounding and sends other electrical signals for testing of the integrated circuits on inverted wafer 225.

10

Holder 260 is attached to the frame of integrated circuit test apparatus 210 and is not attached to an automated system for moving the holder (i.e., wafer) relative to the probe needles. Therefore, the backside viewing, frontside probing system of integrated circuit test apparatus 210 requires the manual re-setting of all probe needles 240 for each
15 time a new die on inverted wafer 225 is to be electrically probe tested. Manual resetting entails an operator unsecuring a clamp, or other securing device, of member 270 from platen 250. The operator would de-attach member 270 from platen 250, move member 270 and secured wafer 225 each time a new die is to be probed by needles 240. After a die is manually aligned with probe needles 240, member 270 is then re-secured to platen
20 250. This will then allow the probe needles to contact a corresponding bonding pad, and stimulate the circuitry on the frontside surface of the wafer while, concurrently, microscope 220 examines any radiation emitted therefrom. A short circuit, implant defect, thin film disturbance, or any other processing problem can be detected by examining the radiation effects of that defect when the circuit is stimulated. Camera 221
25 is used to assist the operator in manually positioning the wafer above the probe needles, so that when member 270 is secured to platen 250, the probe needles will make electrical contact with the corresponding bonding pads. In the case of a flip-chip circuit, the bonding pads include the ball-grid array attributable to a flip-chip bonding arrangement. The resetting process can take up to 15 minutes per probe needle 240, which greatly
30 extends the time required to perform the testing of dice on the wafer.

Optical scanning mechanism 220 is adapted for photoemissions microscopy, wherein it may include, inter alia, magnifying and focusing lens, a electromagnetic radiation source, and a microscope, where the microscope may be a charged coupled device (CCD). Optical scanning mechanism 220 is positioned over the waver so as to being viewing the backside surface of the die that is undergoing testing. The die may be electrically test probed with probe needles 240 in contact with the frontside die I/O contacts to provide ground and power to the integrated circuit to ready standby condition, and/or activated the circuits. Concurrently, during said electrical test probing, optical scanning mechanism 220 is optically scanning the backside surface with a beam of electromagnetic radiation in order to detect photoemission-generated defects, which may occur for shorts, juncture leakages, pinhole defects in the oxide layers, latch-up, hot-carrier gate generation, etc. The scanning beam may be a beam of infrared electromagnetic radiation, since lightly doped silicon as seen from the backside surface of the dice on the wafer is readily transparent to this particular wavelength of electromagnetic radiation.

Fig. 3 is an illustration of one embodiment of the present invention of an automated integrated circuit test. Fig. 3 is a partial cross-sectional view of integrated circuit test apparatus 310 for backside viewing while conducting automated frontside probing of a wafer, which includes holder 360 mounted to three-dimensional translational mechanism 370. Probe station housing 380 is a base support for integrated circuit test apparatus 310. Holder 360 is designed to receive and retain an outer perimeter of a frontside surface of inverted wafer 325. This can be accomplished by using attachment tabs or may be by applying vacuum pressure from the upper surface of holder 360 to the frontside surface of inverted wafer 325. Furthermore, holder 360 has a circular opening in order to allow probe needle 340 access to the frontside surface of inverted wafer 325. Probe needle 340 is an electrically conductive probe. During testing of the wafer, probe needle 340 is positioned to make electrical contact with an I/O bonding pad on the frontside surface of inverted wafer 325. Probe needle 340 is shown to originate from

probe base 330, where probe base 330 may include micropositioning adjusters, which allow for fine adjustment of probe needle 340 in the X, Y, and Z directions.

Camera 321 is preferably attached to platen 350 and enables one to view probe
5 needle 340 in relationship with the wafer for positioning probe needle 340 and/or inverted
wafer 325. Also in another embodiment, the probe needle or needles could originate
from a probe card which has many probe needles emanating around its circumference for
probing the wafer. Furthermore, either probe base 330 or a probe card is electrically
connected to a testing control unit 352, which provides electrical power and grounding
10 and sends other electrical signals for testing of the integrated circuits on inverted wafer
325.

Holder 360 is coupled to a three-dimensional translational mechanism 370.
Three-dimensional translational mechanism 370 can move holder 360 in the three
15 independent X, Y, and Z directions. In one embodiment holder 360 is attached to a pre-
existing wafer chuck of a three-dimensional translational mechanism of a legacy frontside
probe device employing automated probing. Furthermore, three-dimensional translational
mechanism 370 is electrically connected to a testing control unit 352, which allows for
the automatic positioning of the individual die to be tested on inverted wafer 325 by
20 moving holder 360 up and down in the z-plane and incrementally stepping it a
predetermined distance in the xy-plane. Typically, the automated probing process begins
with the probe needles 340, which may be finely adjusted by said micropositioner
adjusters to make contact with appropriate I/O bonding pads of a specific starting die to
be tested on inverted wafer 325. This automated process of repositioning of inverted
25 wafer 325 in relationship with probe needles 340 can be done until a select number of all
of the dice on the wafer have been tested.

Optical scanning mechanism 320 is adapted for photoemissions microscopy,
wherein it may include, *inter alia*, a magnifying and focusing lens, an electromagnetic
30 radiation source, and a camera, where the camera may be a charged coupled device

(CCD) camera. Optical scanning mechanism 320 is positioned over the wafer so as to being viewing the backside surface of the die that is undergoing electrical testing via the probe needles. The die may be electrically test probed with probe needles 340 in contact with the frontside die I/O contacts to provide grounding and powering up of the integrated circuit to ready standby condition, and/or activated the circuits. Concurrently, during said electrical test probing, optical scanning mechanism 320 is optically scanning the backside surface with a beam of electromagnetic radiation in order to detect photoemission-generated defects, which may occur for shorts, juncture leakages, pinhole defects in the oxide layers, latch-up, hot-carrier gate generation, etc..

The inverted arrangement of backside scanning while probing the frontside of a wafer can advantageously be used in testing a complementary metal oxide semiconductor (CMOS) integrated circuit. Generally speaking, CMOS devices do not consume power as, for example, NMOS devices. CMOS devices also have minimal leakage when both the p- and n-transistors of the complementary pair are "off." During the transition time between an input being driven to its rail, a CMOS device will not experience any direct shorting between a power supply and ground. However, if the probe needle stimulates the CMOS circuit with an input level between the voltage rails, and yet the scanning mechanism 320 indicates a short circuit (e.g., an opaque line appearing when the line should be non-opaque). Optical scanning of a backside surface during operation of circuits on the frontside surface via electrical stimuli from probe needles is not only advantageous when determining a short circuit when a short circuit should not exist, but also can indicate defects in gate dielectrics, gate conductors, local interconnects, junction doping (resistance and drive characteristics), and any other defective feature which could harm the operation or reliability of the integrated circuit.

By attaching holder 360 which securely holds wafer 325 to the x, y, and z translational mechanism 370, wafer 325 can be moved automatically relative to probe needles 340. As noted herein, automated probing entails the movement of the wafer by a motor coupled to the translational member 370 and, thus, holder 360 in the interim

between times when each integrated circuit is tested. Accordingly, the system of Fig. 3 allows holder 360 to be set-up so that probe needles 340 are in registry with corresponding bonding pads in the home position. Thereafter, the motor drives the translational member 370 a predefined distance corresponding to the dimensions of each die, and automatically draws the holder downward so that the bonding pads are electrically coupled to the upper-extending probe needles. This is done in an automated, step-and-repeat fashion across the wafer, until all die on the wafer have been probed. Concurrent with one or more of those probe operations, scanning of the backside surface is carried out by scanning mechanism 320.

Camera 321 is used to enable the operator to register translational movement of the wafer so that when the wafer is moved, contact with bonding pads of one die will stay near the relative center of bonding pads of another die, even though the two die may be on opposite ends of the wafer. Fine tuning, or adjustment, of a wafer (and bonding pads) to the probe needles can take place by moving the translational member 370 or the probe base 330 which retains the needles. In many instances, member 370 and base 330 can be rotated by a manual cam mechanism to fine-tune any misalignment between the probe needles and the bonding pads.

An automated step-and-repeat probe mechanism is thereby contemplated. The probe mechanism will move the wafer a predefined amount, which is defined to be consistent as the size of each integrated circuit embodied on the wafer. In other words, the wafer is moved by the translational member 370 in both the x- and y-dimensions governed by the length and width of the die entered into the motor translational unit connected to member 370. Therefore, "consistent" movement of the wafer is predefined, and is herein known to be programmed into the translational motor. By automatically moving the wafer the consistent amount each time, between moments when the frontside surface is probed and the backside surface receives and emits optical energy, the present holder is well-suited to operate upon legacy devices, yet can achieve the aforementioned benefits in an automated setting.

It will be appreciated to those skilled in the art having the benefit of this disclosure that this invention is believed to provide a integrated circuit test apparatus combining a three-dimensional translational mechanism coupled to a wafer holder
5 adapted to allow backside viewing with an optical scanning mechanism of the embedded integrated circuits of an inverted wafer undergoing frontside probing, and a method for such testing of integrated circuits on a wafer. Further modifications and alternative embodiments of various aspects of the invention will be apparent to those skilled in the art in view of this description. It is intended that the following claims be interpreted to
10 embrace all such modifications and changes and, accordingly, the specification and drawings are to be regarded in an illustrative rather than a restrictive sense.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219